

GET THE JOB DONE WITH THIS DUNLITE WELDER GENERATOR POWERHOUSE


This reliable Dunlite welder generator is powerful and built tough.

With a **230 Amp welder** and **10kVA alternator**, this unit has everything you need for all your welding jobs.

OPTIONAL EXTRA

DGX14 Welding Leads

8m long with clamp & holder



GENERATOR	MODEL	DGWGH10ES-2
	RATED VOLTAGE	230V
	FREQUENCY	50Hz
	RATED OUTPUT	8000 Watts
	MAX. OUTPUT	10kVA
ENGINE	ENGINE TYPE	Honda GX630 V-Twin
	HORSEPOWER	20.8HP
	STARTING SYSTEM	Electric

GENERAL	SIZE - LXWXH (MM)	810x545x545
	DRY WEIGHT	160kg
	FUEL TANK CAPACITY	34L
	OPERATING HRS (80% LOAD)	6.15hr
	FUEL CONSUMPTION (80% LOAD)	5.53L/hr
FEATURES	NOISE LEVEL (7M)	75 dbA
	WELDER AMPS OUTPUT RANGE	Adjustable 80 - 230 Amps
	OUTLETS	2 x 15 amp
	CENTRE POINT LIFT	✓
	BRUSHLESS ALTERNATOR	✓



POWERED by
HONDA

Specifications may change without notice

Victoria: Head Office
59 Export Drive
Brooklyn VIC 3012
Ph: +61 3 9316 9799
Fax: +61 3 9314 0909
Email: dunlite@wellcross.com.au

New South Wales
Unit 2/1040 Canley Vale Road
Wetherill Park NSW 2164
Ph: +61 2 9757 5800
Fax: +61 2 9757 5899
Email: nsw@wellcross.com.au

Queensland
Unit 2/55 Christensen Rd
Stapylton QLD 4207
Ph: +61 7 3386 2400
Fax: +61 7 3386 1241
Email: qld@wellcross.com.au

North Queensland
Unit 19/547 Industry Park
547-593 Woolcock St
Mount Louisa, Townsville, QLD 4814
Ph: +61 7 4774 6331
Email: nthqld@wellcross.com.au

Western Australia
Unit 8/235 Camboon Road
Malaga WA 6090
Ph: +61 8 9248 2955
Fax: +61 8 9248 2933
Email: wa@wellcross.com.au

South Australia
Ph: 0417 592 530
Email: bnicholas@wellcross.com.au