



**ELECTRIC START VERSION
AVAILABLE: DGUH5ES-2**

OPTIONAL EXTRAS

- Wheel Kit with Handles
- WorkSafe approved Earth Leakage Outlets
- 25L long range tank
- Lifting bar kit

SPECIFICATIONS

MODEL	DGUH5S-2
POWER RATING	5.8 kVA @ 0.8 pf
ENGINE	Honda GX340
STARTING SYSTEM	Recoil
FUEL TANK	6.1 Litres
OPERATION HOURS	2.6 hrs @ 80% Load
FUEL TYPE	Petrol
DRY WEIGHT	70 kg
DIMENSION (LxWxH)	735 x 545 x 545 mm
NOISE LEVEL	68 dBA @ 7m

DGUH5S-2

5.8 kVA Honda Powered Generator

A popular choice and a great all-rounder.

Features:

- Reliable Honda GX340 engine
- 2 x 15 Amp outlets
- Heavy duty frame
- NSM brushless alternator



Specifications and product availability subject to variation without notice.

Victoria: Head Office

59 Export Drive
Brooklyn VIC 3012
P: +61 3 9316 9799
F: +61 3 9314 0909
E: dunlite@wellcross.com.au

New South Wales

Unit 2/1040 Canley Vale Road
Wetherill Park NSW 2164
P: +61 2 9757 5800
F: +61 2 9757 5899
E: nsw@wellcross.com.au

Queensland

Unit 2/55 Christensen Rd
Stapylton QLD 4207
P: +61 7 3386 2400
F: +61 7 3386 1241
E: qld@wellcross.com.au

North Queensland

Unit 19/547 Industry Park
547-593 Woolcock St
Mount Louisa, Townsville, QLD 4814
P: +61 7 4774 6331
E: nthqld@wellcross.com.au

Western Australia

Unit 8/235 Camboon Road
Malaga WA 6090
P: +61 8 9248 2955
F: +61 8 9248 2933
E: wa@wellcross.com.au

South Australia

Ph: 0417 592 530
E: bnicholas@wellcross.com.au