DUNLITE Generators

Powering the Nation Since 1936





POWERED by HONDA

DGUH20ES-2

20 kVA Honda Powered Generator

From the farm to the building site, this massive petrol generator with 20 kVA of raw power will handle anything you throw at it. Powered by the robust Honda iGX800 engine, you know that you can rely on this generator when you need it.

Features:
- Electric start
- Electronic Fuel Injection
- 2 x 32 Amp 3 pin outlets with circuit breaker
- 1 x 15 Amp 3 pin outlet with circuit breaker
- Long range fuel tank
- Battery
- Centre point lift

SPECIFICATIONS

MODEL	DGUH20ES-2
POWER RATING	20 kVA @ 0.8 pf
ENGINE	Honda iGX800
STARTING SYSTEM	Electric
FUEL TANK	34 Litres
OPERATION HOURS	6.15 hrs @ 80% Load
FUEL TYPE	Petrol
DRY WEIGHT	180 kg
DIMENSION (LxWxH)	876 x 546 x 700 mm
NOISE LEVEL	75 dBA @ 7m

GX Engine 3 YEAR WARRANTY

HONDA AUSTRALIA APPROVED

Specifications and product availability subject to variation without notice.

Victoria: Head Office
59 Export Drive
Brooklyn VIC 3012
P: +61 3 9316 9799
F: +61 3 9314 0909
E: dunlite@wellcross.com.au

New South Wales
Unit 2/1040 Canley Vale Road
Wetherill Park NSW 2164
P: +61 2 9757 5800
F: +61 2 9757 5899
E: nsw@wellcross.com.au

Queensland
Unit 2/55 Christensen Rd
Stapylton QLD 4207
P: +61 7 3386 2400
F: +61 7 3386 1241
E: qld@wellcross.com.au

North Queensland
Unit 19/547 Industry Park
547-593 Woolcock St
Mount Louisa, Townsville, QLD 4814
P: +61 7 4774 6331
E: nthqld@wellcross.com.au

Western Australia
Unit 8/235 Camboon Road
Malaga WA 6090
P: +61 8 9248 2955
F: +61 8 9248 2933
E: wa@wellcross.com.au

South Australia
Ph: 0417 592 530
E: bnicholas@wellcross.com.au

dunlite.com.au

1300 555 253